

### Locations (Indiana v3.6)

Last Modified on 12/23/2024 12:50 pm CST

You are viewing a previous version of this article. See the Indiana Ed-Fi article for the most current information.

Object Triggering Logic | School Exclude, Calendar Exclude, Resource Toggle and Resync Logic | Natural Key Changes, Cascading Updates, and Deletes Logic | Scope Year Logic | Event Queue Detail | Object Data Elements

This entity represents the physical space where students gather for a particular class/section. The location may be an indoor or outdoor area designated for the purpose of meeting the educational needs of students.

#### **Object Triggering Logic**

This table describes logic for triggering syncing of this object.

Action	Trigger
Post	When a new Room is created and saved.  • Do not send if the School is marked as Exclude.
Post	When a Room Name is changed and saved.
Put	When the room number changes.
Delete	When a Room is deleted.
Delete/Post	When a Room Name is changed and saved.
Delete/Post	When there are two rooms with the same natural key and 1 is deleted, the other record will post with the remaining records data.

# School Exclude, Calendar Exclude, Resource Toggle and Resync Logic

This table describes the School Exclude, Calendar Exclude, Resource Toggle and Resync logic of this object.

Action	Trigger
None	If a resource is toggled to 'OFF' after data has sent, all sent data will remain in the ODS but no new data will send.



Action	Trigger
Delete	If a resource is toggled to 'OFF" after data has sent and an action is performed that would trigger a delete, that data will remain in the ODS until a resync is done.
Resync	If a record is in the Ed-Fi Identity Mapping table and not in the ODS, it will be deleted from the Ed-Fi Identity Mapping table.
Resync	If a record is in the ODS and it does not have a matching record in Campus or the Ed- Fi Identity Mapping table, it will be deleted from the ODS.
Resync	If a mapping is changed in Resource Preferences, a resync will need to be done to reflect the changes.

## Natural Key Changes, Cascading Updates, and Deletes Logic

This table describes the Natural Key Changes/Cascading Updates and Deletes logic of this object.

Action	Trigger
Delete/Post	If any of the following changes in the Schools resource:  • If the School Number/Ed-Fi School Number changes, a delete/post will occur with the cascading deletes from the School ID Change triggers.
Delete/Post	If the Room Name changes.

#### **Scope Year Logic**

### Logic

Rooms are not aligned to a year so all Rooms will send to each scoped year.

Data will only send for years that have valid configuration.

#### **Event Queue Detail**

<b>Campus Table</b>	Ed-Fi Action	Fields
rooms	Post/Put/Delete	The primary table used for sending data for this resource.

#### **Object Data Elements**

This table describes data elements sent within the Locations resource.



Data Element Label	Business Requirement	Business Rules	M, C or O	Location
id	The unique identifier of the resource.		М	
classroomIdentificationCode	A unique number or alphanumeric code assigned to a room by a school, school system, state, or other agency or entity.	Reports the Room Name.	М	System Administration > Resources > Resources > Rooms room.name
schoolReference	A reference to the related School resource.	Reports the fields that are part of the Natural Key for the School resource.	M	System Administration > Resources > School > State School Number  System Administration > Resources > District Information > State District Number  district.Number school.number
maximumNumberOfSeats	The highest number of seats the class can maintain.	<ol> <li>Reports the Capacity.</li> <li>If blank, does not report.</li> </ol>	0	System Administration > Resources > Resources > Capacity  room.capacity
optimalNumberOfSeats	The number of seats that is most favorable to the class.	Optional, does not report.	0	



Data Element Label	Business Requirement	<b>Business Rules</b>	M, C or O	Location
_etag	A unique system-generated value that identifies the version of the resource.	Optional, does not report.	0	